

V-Turnstile with local access control



possible application fields

smaller company premises
smaller building site

Technical data of the access control

Up to 3000 users per access control
Protection class IP 67
Reading distance 5-10 cm
Dimensions 140x70x16mm
Operating temperature -20 to 70°C
RFID reader with 10 pre-programmed chips
Alternative opening by fingerprint or numerical code
Additional chips can be ordered at extra cost
Local creation + deletion of chips also possible in bulk
The reader can be installed on one or both sides.

Fail-Open Fail-Close

When the turnstile is connected to the power supply, both directions are closed by default. and can be opened by holding a chip in front of them. With the help of the profile cylinders on the underside of the roof, the RFID readers can be deactivated to allow permanently free access.

In the event of a power failure or use without power, access from the public area is blocked (can be opened with a key) and it is always possible to leave the grounds.